## **LINOVISION**

# IOT-C100-LORA

Modbus RS485 to LoRaWAN® Converter



Uptaded on July. 8, 2022



IOT-C100-LORA is an IoT controller used for remote control and data acquisition from Modbus RS485 devices via LoRaWAN® networks. It can read up to 16 Modbus RTU devices and support Modbus transparent transmission between server and RS485 devices as a Modbus to LoRaWAN® converter. Besides, it supports multiple trigger conditions and actions which can work autonomously even when the network dropped. Combining with Linovision IoT Cloud solution, it can monitor and control remote assets via web server or mobile App easily.

IOT-C100-LORA is widely used in indoor applications like smart metering, smart cities, building automation, etc.

### Application Example



#### Features

- Support reading 16 Modbus registers, can connect up to 16 Modbus devices
- Ultra-wide-distancetransmission up to line of sight of 15 km
- Multiple triggering conditions and actions
- Embedded watchdog for device working stability
- Support Linovision LoRa D2D protocol to enable ultra-lowlatency and directly control without LoRaWAN® gateway
- Compliant with standard LoRaWAN® gateways and network servers
- Quick and easy management with Linovision IoT Cloud solution

## Specifications

| Wireless Transmission                                     |   |
|---|---|
| Technology  | LoRaWAN®, LoRa D2D                                      |
| Antenna   | Internal Antenna  |
| Frequency   | CN470/IN865/EU868/RU864/US915/AU915/KR920/AS923-1&2&3&4 |
| Tx Power  | 16dBm (868 MHz)/22dBm (915 MHz)/19dBm (470 MHz)         |
| Sensitivity   | -137dBm@300bps  |
| Mode  | OTAA/ABP Class C  |
| Advanced Feature  | LoRa D2D Controller, LoRa D2D Agent                     |
| Data Interface  |   |
| Port  | 1 ×RS485  |
| Connector   | 3.5 mm Terminal Block                                   |
| Terminal Resistor   | $1 \times 120 \Omega$ Resister Switch                   |
| Baud Rate   | 1200~115200 bps   |
| Protocol  | Modbus RTU, support reading 16 register values          |
| Others  |   |
| Configuration Port  | 1 ×Type–C   |
| Reset Button  | 1 ×Reset Button (Internal)                              |
| LED Indicator   | 1 ×System   |
| Physical Characteristics                                  |   |
| Power Connector   | 3.5 mm Terminal Block                                   |
| Power Supply  | 1. 5-24VDC by Terminal Block                            |
|   | 2. 5 VDC by Type-C Port                                 |
| D 6 .:  | OF W  |
| Power Consumption   | <0.5 W  |
| Material & Color  | PC+ABS, White   |
|   |   |
| Material & Color  | PC+ABS, White   |
| Material & Color<br>Ingress Protection                    | PC+ABS, White IP30                                      |
| Material & Color Ingress Protection Operating Temperature | PC+ABS, White IP30 -20°C~ 60°C (-4°F to +140°F)         |